

Why compromise, when you have a choice. Choose genuine. Say no to non-genuine.



Technical **Specifications**

	HL-B2080DW
Key Functions	Automatic 2-sided Printing With Wireless Connectivity
PRINT FUNCTIONS	
Print Speed (A4/Letter)	Up to 34 / 36 ppm
2-sided Printing	Yes
Print Resolution	600 x 600 dpi; HQ1,200 (2,400 x 600 dpi) quality; 1,200 x 1,200 dpi
First Printout Time (Ready)	Less than 8.5 secs
Max. Monthly Duty Cycle	Up to 15,000 pages
PAPER HANDLING	
Input Capacity	250 sheets
Manual Feed Slot	1 sheet
Output Capacity [^]	150 Sheets Face Down
Media Weights	60 to 230g/m² (Using Manual Feed Slot)
Media Size	A4, Letter, A5, A5(Long Edge), A6, Executive, Legal, Folio, Mexico Legal, India Legal
CONNECTIVITY	
Interface	Hi-Speed USB 2.0, 10Base-T/100Base-TX, IEEE 802.11b/g/n (Infrastructure Mode), IEEE 802.11g/n (Wi-Fi Direct)
Mobile Solutions	AirPrint, Mopria, Google Cloud Print, Brother iPrint&Scan
Wi-Fi Direct	Yes
OTHERS	
Processor Speed	600MHz
Memory	64MB
Emulation	PCL6
Display	16 characters x 1 line
OS Compatibility	Windows 7 SP1, 8, 8.1, 10, Server 2008, Server 2008 R2, Server 2012, Server 2012 R2, Server 2016, macOS v10.10.5, 10.11.x, 10.12.x (Download only), CUPS, LPD/LPRng (x86/x64 environment)
Utilities & Solutions	BRAdmin Light: Windows (by Download); BRAdmin Pro3: Windows (by Download)
Energy Saving Mode	Energy Star
Power Consumption (Printing / Sleep)	510W / 6.0W
Power Source	220-240V, AC 50/60Hz
Noise Level	LpAm = 49 dB(A)
SUPPLIES	
Standard Yield Toner (TN-B021)*	Approx. 2,600 Pages
Drum (DR-B021)	Approx. 12,000 Pages
Inbox Toner	Approx. 2,600 Pages
DIMESIONS & WEIGHT	
Dimension (W x D X H)	356 x 360 x 183 mm
Weight	7.4kg

[^]Actual output tray capacity may vary depending on environmental conditions







Brother strongly recommends the use of genuine Brother consumable products only. Benefits include better quality print, greater yields per consumable, protection of your machine from damages and achievement of optimum performance. As a precaution, please note that your machine warranty may not cover any damages arising from the use of non-genuine consumables.



^{*}In accordance with ISO/IEC 19752